

## ZG RETROFIT BOX M

Art. no. 96684001

### Application

The ZG RETROFIT BOX M and ZG RETROFIT BOX W are accessories designed to interface between non-Zhaga D4i luminaires and a Zhaga-D4i wireless controller. These accessories can be either attached to a mast (M version) or to wall (W version).

The ZG RETROFIT BOX M & W are part of THORN UrbaSens PLAY control system.

The ZG RETROFIT BOX M & W are only compatible with RF-Controller ZG bDW 96636993



### Functional description

Functional description:

- Integrated 24V Power supply
- Integrated DALI bus power supply
- Integrated 10kV surge protection
- ZU Zhaga book 18 ed 3.0 socket

#### Technical data

|                         |   |
|-------------------------|---|
| Nominal input voltage   | 220-240V  |
| Permitted input voltage | 198-264V  |
| Outputs                 | 1 D4i compliant output with integrated bus power supply (DA+/DA-) |
| Power consumption       | Max 8 DALI loads  |
| Ambient temperature     | -20°C to +50°C  |
| Protection type         | IP66  |